



Datasheet for Models:

KF1R

KF1

The new-look, cost-effective Firex cable-harness range of smoke and heat alarms – manufactured and supplied by Kidde, with the reassurance of a leading global manufacturer.



Lic No: KM524754
BS EN 14604: 2005

Kidde Firex – 2012 model numbers

(previous models in brackets)

Back-up type	Sealed-in rechargeable	Loose battery
Alarm type		
Ionisation smoke	KF1R (4881)	KF1 (4870)
Optical smoke	KF2R (4985)	KF2 (4973)
Heat	KF3R (4892)	KF3 (4899)

230V Mains Ionisation Smoke Alarms

Key Features

Firex hard-wired smoke and heat alarms all have a full 6-year guarantee and are BSi Kitemarked to reinforce the consistent quality provided by the world's largest manufacturer. Ionisation and optical models are complemented by heat alarms for situations unsuitable for smoke alarms, such as kitchens and garages.

- Single 'Hush' and 'Test' button
- Choice of sealed-in rechargeable (three Panasonic lithium cells) or loose battery back-up ranges
- Cable harness type connection and interconnectable up to 24 units
- Supplied with base-plate

Applications

Both models are mains powered (for professional installation) with back-up power, complying with current minimum requirements of the relevant Building Regulations for new housing, i.e. Grade D (BS5839, Part 6).

Ionisation Smoke Alarms are for use where a fast flaming fire (for example, electrical equipment igniting) is more likely to be a hazard than a slow, smouldering one, such as from furniture and bedding. They are more prone to nuisance alarms from cooking particles and steam near kitchens. They contain a very small amount of Americium 241 radioactive material, which may be a consideration for future disposal.

Technical Specification

Sensor	Ionisation, circular metallic chamber with 24 slot entry inlet portals
Certification	BSi Kitemarked to BS EN 14604: 2005
Source	Americium 241 (≤ 1.0 microcurie, 37kBq)
Button Test	Simulates the effect of smoke within the sensing chamber, checks electronics and sounder
Automatic Self-Test	Circuitry is tested and unit single beeps (chirps) if fault is detected
Supply Voltage	230V AC, 50Hz (nominal UK Voltage)
Power Consumption	Typical 50mA
Connection	Push fit/snap in grip type connector with 150mm long flying leads (supplied)
Battery back-up	(Model KF1) 1 off 9 Volt Alkaline Battery 522/6LR61 (User Replaceable) (Model KF1R) 3 off 3 Volt Rechargeable Lithium Cells Panasonic UL2330 (User Non replaceable)



Thank you for reading this data sheet.

For pricing or for further information, please contact us at our UK Office, using the details below.



UK Office

Keison Products,

P.O. Box 2124, Chelmsford, Essex, CM1 3UP, England.

Tel: +44 (0)330 088 0560

Fax: +44 (0)1245 808399

Email: sales@keison.co.uk

Please note - Product designs and specifications are subject to change without notice. The user is responsible for determining the suitability of this product.